

LIGHTING CONSOLE SYSTEM

CONSOLE

CX-12 DMX DIMMING CONSOLE

96 CH. Programmable Dimming Console

Signal output: (1) DMX512 (2) 24 channe analog signal 0-10V

Direct control to 96 channels (4 pages). Control CH. 97-512 by patch function

96 scenes (every page key can save 24 scenes)

24 programmable chaser pattern

Each chaser program can include 64 steps at most 2 sets of individual cross faders

The pre-programmed data can be saved into the external memory card (option)

DATA

Power input AC 100-240V, 50-60Hz, 0.5A

DMX signal output channel 512 channels, CH97-512 controlled by patch

DMX signal input/ output DMX512/ 1990

DMX signal connection XLR 5 Pin

Analog signal output DC 0-10V

Analog output channel

24 channels, Pin 1-24; CH1-24, Pin 25: GND

Analog signal connection D-Type plug 25 Pin (M)

Gooseneck lamp connection XLR 3 Pin, DC+ 12V 250mA

Dimension: 482(L) x 355(W) x 125(H) mm

Rack size 19" 8U rack mountable

Weight: 5 KG



CX-3 DIMMING CONSOLE

Signal output: (1) DMX512 (2) 24 channe analog signal 0-10V for 24 channels

Can control 512 channels

Can program and save up to 40 sets scenes

Can program and save 12 sets scenes (with hot keys 1-12)

With chase function

Can set up to 99 steps in each chase program

2 independent CROSS FADE to change scenes

Audio control

DATA

Power input DC 12V/ 1A

DMX connection XLR 5 Pin

MIDI signal input maximum input AC 100mV

Dimension: 482(W) x 176(H) x 95(D) mm

Weight: 4 KG

